

NFC READER

Beacons & sensors reader for PC

BENEFITS

- Compatible with BLE, LORA, MESH, QUUPPA ELA Innovation's beacons & sensors
- Adapted to harsh environment



TECHNICAL SPECIFICATIONS

OPERATING MODE

Device Driver Operating System Support	Windows® 10 / 11 - Linux®, Mac OS®, Solaris, Android™ 3.1 and later
Contactless Smart Card Interface	All ELA 2.4GHz Beacons (including BLE/WIREPAS/QUUPPA)
Application Programming Interface	Device Manager software
USB Host Interface	Connector Type: USB Type-A

CERTIFICATIONS

EN 60950/IEC 60950, ISO 14443, ISO 18092, ISO 7816 (SAM Slot), USB Full Speed, PC/SC, CCID, CE, FCC, RoHS 2, REACH J-LIS (Japan), VCCI (Japan), KC (Korea), MIC (Japan), Microsoft® WHQL, NFC Forum Certification Mark, Felica Performance Certification

MECHANICAL INFORMATION

Dimensions	98.0 mm (L) × 65.0 mm (W) × 12.8 mm (H)
Weight	81g
Operating temperature	0 °C – 60 °C ; humidity <90% (non-condensing)
Built-in peripherals	LED: 1 bi-color Red and Green Buzzer: Monotone

MECHANICAL DRAWING

